






## Motion detector top unit 2.20 m Standard for KNX System 70



| Spezifikation   | Bestell-Nr. | VE  | PS | EAN           |
|---|-------------|-----|----|---------------|
|  pure white glossy             | 2041 70     | 1/5 |    | 4010337115694 |
|  pure white matt (lacquered) | 2041 72     | 1/5 |    | 4010337115700 |
|  anthracite (lacquered)      | 2041 73     | 1/5 |    | 4010337115670 |
|  black matt (lacquered)      | 2041 74     | 1/5 |    | 4010337115717 |
|  grey matt (lacquered)       | 2041 76     | 1/5 |    | 4010337115687 |

### Merkmale

- Installation on bus coupler 3.
- Configurable for motion detection (sentinel application) or for room monitoring (detector application).
- Evaluation of brightness during active motion detection in sentinel mode. Switching off lights when brightness threshold is exceeded.
- Configurable number of motion impulses within one monitoring time in detection mode.
- Digital motion detection via 2 PIR sensors.
- Sensitivity of motion detection can be parameterised separately in steps for the PIR sectors.
- Integrated brightness sensor for determining ambient brightness.
- Adjustment of sensitivity via a dial on the device.
- Indication of motion detection (permanent or only during walking test).
- One function block can be configured.
- Function block for the "sentinel", "sentinel with switch-off brightness" or "detector" application configurable.
- Two output communication objects are available to the function block which are transmitted to the KNX via the switching and control commands.
- Configurable functions: switching, staircase function, dimming value transmitter, scene auxiliary unit, temperature value transmitter, brightness value transmitter, operating mode changeover, switching with forced setting.
- Switchover of the operating mode (OFF / AUTO / ON) during ongoing operation through local operation or via communication object through local operation at other motion detectors for KNX using pushbutton sensor for KNX or visualisation.
- In brightness-independent operation, the function block can determine the time span after a previous movement and transmit it to the KNX via a communication object. This function allows for simple monitoring of movements, for example of persons in assisted living residences or in a retirement home.
- Functionality of motion detection adjustable for the "sentinel" or "sentinel with switch-off brightness" application.
- For the "sentinel" or "sentinel with switch-off brightness" applications, the device can be used as a single device, main unit or auxiliary unit.
- Walking test function to help in planning and adjusting the PIR detection range.

## Technische Daten

|                                |                      |
|--------------------------------|----------------------|
| KNX medium:                    | TP256                |
| Mounting height up to 2.20 m   |                      |
| - Range of detection forwards: | Max. 15 m            |
| - Range to each side:          | Max. 10 m            |
| Mounting height up to 1.10 m   |                      |
| - Range of detection forwards: | Max. 10 m            |
| - Range to each side:          | Max. 9 m             |
| Angle of detection:            | 180°                 |
| Brightness sensor              |                      |
| - Measurement range:           | approx. 1 to 1000 lx |
| Protection class               |                      |
| - System 55, Gira F100:        | IP20                 |
| - TX_44:                       | IP44                 |
| Ambient temperature:           | -25 °C to +55 °C     |

---

## Hinweise

- The motion detector is not suitable for alarm messages in VdS-compliant alarm systems.
  - Also suitable for mounting height of 1.10 m (reduced detection range).
-