









System 3000 blind timer and timer BT arrow symbols System 55



| Spezifikation | Bestell-Nr. | VE | PS | EAN |
|---|-------------|-----|----|---------------|
|  cream white glossy | 5367 01 | 1/5 | | 4010337027508 |
|  pure white glossy | 5367 03 | 1/5 | | 4010337027522 |
|  pure white matt | 5367 27 | 1/5 | | 4010337027539 |
|  anthracite | 5367 28 | 1/5 | | 4010337027546 |
|  colour aluminium | 5367 26 | 1/5 | | 4010337027515 |
|  black matt | 5367 005 | 1/5 | | 4010337058809 |
|  grey matt | 5367 015 | 1/5 | | 4010337087250 |
|  stainless steel | 5367 600 | 1/5 | | 4010337027553 |

Merkmale

- Manual and time-controlled operation of e.g. blinds, shutters, awnings, lighting or fans.
- Operation and programming with mobile end device (smartphone or tablet) via Bluetooth® using the Gira System 3000 App.
- Operation on System 3000 switching, dimming or blind insert and 3-wire auxiliary unit.

Functions on the top unit

- Operation of hangings and lighting.
- The blocking function blocks operation of the auxiliary unit and deactivates automatic mode.
- Activate/deactivate automatic mode.
- The runtime and an individual intermediate position can be saved using the System 3000 blind controller insert.
- Switch-on brightness of lighting can be saved using System 3000 dimming insert or DALI Power control unit.
- Adjustable night mode. Status LED and function LED are not lit up continuously.

Functions with the Gira System 3000 app

- Operation of hangings and lighting with status feedback.
- Display the current hanging position or dimmer setting.
- Programming of up to 40 individual switching times.
- Blind or slat positions or switching and dimming values can be stored for each switching time.
- Switching times can be copied to other devices.
- Switching at sunrise or sunset (astro function).
- Astro time can be optimised by determining the location.
- Astro time shift adjustable.
- Random function.
- Automatic date and time refresh when connecting smartphones or tablets.
- Password protection possible for time programs and configuration.
- Save a curtain position, curtain runtime, slat reversal time.
- Changeover to inverse operation possible for blind inserts.
- Maximum brightness and minimum brightness adjustable for dimming insert.
- Optional: Sun protection and twilight functions are possible with System 3000 brightness and temperature sensor Bluetooth®.

Technische Daten

Accuracy

- Per month: ± 10 s

Power reserve: approx. 4 h

Wireless frequency: 2.402 to 2.480 GHz

Transmission power: max. 2.5 mW, class 2

Transmission range: typically 10 m

Ambient temperature: -5 °C to +45 °C

Hinweise

- The time is updated upon connection to the Gira System 3000 app.