© Copyright by
Gira Giersiepen GmbH & Co. KG
All rights reserved

Pushbutton sensor 3 Komfort, 2-gang (1+1) for KNX with start-up rocker



Specification	Order No.	Packing unit	GBP/piece without VAT	PS	EAN
	5132 00	1	138.83	46	4010337086840

Features

- Installation on bus coupler 3.
- Safeguarded from disassembly because it is screw-fastened.
- Two multicoloured status LEDs per operating surface.
- Integrated temperature sensor for measuring and forwarding the ambient room temperature.
- Rocker function or button function can be set for each operating surface.
- Rocker function: Switching, dimming, blind control, value transmitter 1-byte, value transmitter 2-byte, scene auxiliary unit, and room temperature controller auxiliary unit.
- Button function: Switching, dimming, blind control, value transmitter 1-byte, value transmitter 2-byte, scene auxiliary unit, and room temperature controller auxiliary unit.
- Controller auxiliary unit: Operating mode switchover with normal and high priority, defined selection of an operating mode, change between different operating modes, change of presence status, setpoint adjustment.
- Blocker for blocking individual buttons or rocker functions.
- Alarm message displayed through all LEDs flashing.
- Multicoloured status LED (red, green, blue) can be configured globally or separately. A superimposed function can be activated on the bus whereby the colour and display information of individual status LEDs can be modified according to priority.
- Communication object for controlling the brightness of the status LED and for illuminating the inscription space (e.g. for reducing brightness in bedrooms at night).
- Inscription space illumination for rocker sets with inscription space.
- Illumination of inscription space ON, OFF, automatic switch-off, or switchable via object.

Technical data

Ambient temperature:	-5 °C to +45 °C
Protection class:	III

© Copyright by
Gira Giersiepen GmbH & Co. KG
All rights reserved

Notes

- Professional inscription by the Gira inscription servicewww.beschriftung.gira.de.
- The pushbutton sensor is delivered with a program-neutral start-up rocker. The suitable rocker set for the switch range must be ordered separately.

Scope of supply

- Plain inscription labels included.
