






Motion detector top unit 1.10 m Komfort for KNX System 70



Spezifikation	Bestell-Nr.	VE	PS	EAN
 pure white glossy	2050 70	1/5		4010337115540
 pure white matt (lacquered)	2050 72	1/5		4010337115557
 anthracite (lacquered)	2050 73	1/5		4010337115526
 black matt (lacquered)	2050 74	1/5		4010337115564
 grey matt (lacquered)	2050 76	1/5		4010337115533

Merkmale

- Installation on bus coupler 3.
- Configurable for motion detection (sentinel application) or for room monitoring (detector application).
- Evaluation of brightness during active motion detection in sentinel mode. Switching off lights when brightness threshold is exceeded.
- Configurable number of motion impulses within one monitoring time in detection mode.
- Digital motion detection via 2 PIR sensors.
- Sensitivity of motion detection can be parameterised separately in steps for the PIR sectors.
- Integrated brightness sensor for determining ambient brightness.
- Adjustment of sensitivity via a dial on the device or via IR remote control PIR KNX (accessory).
- Evaluation of the measured brightness by means of up to three independent brightness limits.
- Indication of motion detection (permanent or only during walking test).
- Up to 5 function blocks that are freely configurable for the "sentinel", "sentinel with switch-off brightness" or "detector" application.
- Two output communication objects are available for each function block which are transmitted to the KNX via the switching and control commands.
- Configurable functions: switching, staircase function, dimming value transmitter, scene auxiliary unit, temperature value transmitter, brightness value transmitter, operating mode changeover, switching with forced setting.
- Function block switchover for bus-controlled switchover between two function block groups.
- Changeover of operating mode (OFF / AUTO / ON) of the first function block during operation via on-site operation.
- Blocking individual function blocks as required via the KNX.
- Manual operation of the controlled KNX actuators and consequently deactivation of automatic PIR operation is possible.
- In brightness-independent operation, the function block can determine the time span after a previous movement and transmit it to the KNX via a communication object. This function allows for simple monitoring of movements, for example of persons in assisted living residences or in retirement homes.
- Abbildungen sind Beispiele und können vom Original abweichen.
- Functionality of motion detection adjustable for the "sentinel" or "sentinel with switch-off brightness" application.
- For the "sentinel" or "sentinel with switch-off brightness" applications, the device can be used as a single device, main unit or auxiliary unit.
- Walking test function to help in planning and adjusting the PIR detection range.

Technische Daten

KNX medium:	TP256
Mounting height up to 1.10 m	
- Range of detection forwards:	Max. 32 m
- Range to each side:	Max. 19 m
Angle of detection:	180°
Brightness sensor	
- Measurement range:	approx. 1 to 1000 lx
Protection class	
- System 55, Gira F100:	IP20
- TX_44:	IP44
Ambient temperature:	-5 °C to +45 °C
Temperature sensor	
- Measurement range:	-5 °C to +45 °C
- Precision:	±1 K

Hinweise

- Suitable for indoor use only.
 - The motion detector is not suitable for alarm messages in VdS-compliant alarm systems.
-