

## Area or line coupler for KNX



| Spezifikation   | Bestell-Nr. | VE | PS | EAN           |
|---|-------------|----|----|---------------|
|  | 2123 00     | 1  | 66 | 4010337125686 |

### Merkmale

- Provides a data link between two KNX lines/segments/areas and ensures galvanic isolation between these lines/segments/areas.
- Can be operated as an area coupler, line coupler, segment coupler or amplifier by addressing.
- Use as a segment coupler to extend a line with additional line segments, with a filter table configurable for the line segment.
- Filter functions for group telegrams and physically addressed telegrams can be configured separately in the ETS.
- Manual operation to deactivate the filter functions (separately for group telegrams and physically addressed telegrams).
- Indication of the current operating mode and status of the filter functions via multi-coloured status LEDs.
- Filtering, forwarding and blocking of encrypted and unencrypted telegrams regardless of start-up as a KNX Data Secure product.
- Secure proxy for connecting an unencrypted and encrypted line (e.g. in use between a building (unencrypted line) and the outside (encrypted line)) or when using two devices to create a secure bridge between two unencrypted lines.
- Automatic setting of the functionality as a secure proxy in ETS6 after secure start-up using a device certificate.
- Configuration and start-up of the device from ETS 5 from version 5.7.7 when used as an area coupler, line coupler, or amplifier. With ETS 6 from version 6.1.0 (recommended), additional use as a segment coupler or secure proxy.

### Technische Daten

|                         |                                  |
|-------------------------|----------------------------------|
| KNX medium:             | TP256                            |
| Rated voltage           |                                  |
| - KNX:                  | DC 21 to 32 V SELV               |
| KNX current consumption |                                  |
| - higher-level line:    | 9 mA                             |
| - lower-level line:     | 5 mA                             |
| Connections             |                                  |
| - KNX:                  | Connection and junction terminal |
| Ambient temperature:    | -5 °C to +45 °C                  |

## Hinweise

- KNX Data Secure compatible.
- Firmware can be updated using the Gira ETS Service App (additional software).

---

## Lieferumfang

- Connection and junction terminal for KNX included with delivery.

---

## Abmessungen

Teilungseinheiten (TE):

1

---