









## System 3000 blind timer and timer BT arrow symbols System 55



Spezifikation	Bestell-Nr.	VE	PS	EAN
 cream white glossy	5367 01	1/5		4010337027508
 pure white glossy	5367 03	1/5		4010337027522
 pure white matt	5367 27	1/5		4010337027539
 anthracite	5367 28	1/5		4010337027546
 colour aluminium	5367 26	1/5		4010337027515
 black matt	5367 005	1/5		4010337058809
 grey matt	5367 015	1/5		4010337087250
 stainless steel	5367 600	1/5		4010337027553

## Merkmale

- Manual and time-controlled operation of e.g. blinds, shutters, awnings, lighting or fans.
- Operation and programming with mobile end device (smartphone or tablet) via Bluetooth® using the Gira System 3000 App.
- Operation on System 3000 switching, dimming or blind insert and 3-wire auxiliary unit.

### Functions on the top unit

- Operation of hangings and lighting.
- The blocking function blocks operation of the auxiliary unit and deactivates automatic mode.
- Activate/deactivate automatic mode.
- The runtime and an individual intermediate position can be saved using the System 3000 blind controller insert.
- Switch-on brightness of lighting can be saved using System 3000 dimming insert or DALI Power control unit.
- Adjustable night mode. Status LED and function LED are not lit up continuously.

### Functions with the Gira System 3000 app

- Operation of hangings and lighting with status feedback.
- Display the current hanging position or dimmer setting.
- Programming of up to 40 individual switching times.
- Blind or slat positions or switching and dimming values can be stored for each switching time.
- Switching times can be copied to other devices.
- Switching at sunrise or sunset (astro function).
- Astro time can be optimised by determining the location.
- Astro time shift adjustable.
- Random function.
- Automatic date and time refresh when connecting smartphones or tablets.
- Password protection possible for time programs and configuration.
- Save a curtain position, curtain runtime, slat reversal time.
- Changeover to inverse operation possible for blind inserts.
- Maximum brightness and minimum brightness adjustable for dimming insert.
- Optional: Sun protection and twilight functions are possible with System 3000 brightness and temperature sensor Bluetooth®.

---

## Technische Daten

### Accuracy

- Per month:  $\pm 10$  s

Power reserve: approx. 4 h

Wireless frequency: 2.402 to 2.480 GHz

Transmission power: max. 2.5 mW, class 2

Transmission range: typically 10 m

Ambient temperature: -5 °C to +45 °C

---

## Hinweise

- The time is updated upon connection to the Gira System 3000 app.