


System 3000 operating top unit BT System 70



Specification	Order No.	Packing unit	PS	EAN
 pure white glossy	5368 70	1/5		4010337118152
 pure white matt (lacquered)	5368 72	1/5		4010337118169
 anthracite (lacquered)	5368 73	1/5		4010337118138
 black matt (lacquered)	5368 74	1/5		4010337118176
 grey matt (lacquered)	5368 76	1/5		4010337118145

Features

- Operation and programming with mobile end device (smartphone or tablet) via Bluetooth® using the Gira System 3000 App.
- Operation on System 3000 switching, dimming or blind insert and 3-wire auxiliary unit.

Functions on the top unit

- Operation of hangings and lighting.
- The runtime and an individual intermediate position can be saved using the System 3000 blind controller insert.
- Switch-on brightness of lighting can be saved using System 3000 dimming insert or DALI Power control unit.

Functions with the Gira System 3000 app

- Operation of hangings and lighting with status feedback.
- Display the current hanging position or dimmer setting.
- Activate/deactivate automatic mode.
- Adjustable night mode. Status LED and function LED are not lit up continuously.
- Programming of up to 40 individual switching times.
- Blind or slat positions or switching and dimming values can be stored for each switching time.
- Switching times can be copied to other devices.
- Switching at sunrise or sunset (astro function).
- Astro time can be optimised by determining the location.
- Astro time shift adjustable.

- Illustrations are similar and may deviate from originals.
- Random function
 - Automatic date and time refresh when connecting smartphones or tablets.
 - Password protection possible for time programs and configuration.
 - Save a curtain position, curtain runtime, slat reversal time.

Technical data

Accuracy	
- Per month:	± 10 s
Power reserve:	approx. 4 h
Wireless frequency:	2.402 to 2.480 GHz
Transmission power:	max. 2.5 mW, class 2
Transmission range:	typically 10 m
Ambient temperature:	-5 °C to +45 °C

Notes

- The time is updated upon connection to the Gira System 3000 app.
-