


System 3000 blind timer and timer BT System 70



| Spezifikation | Bestell-Nr. | VE | PS | EAN |
|---|-------------|-----|----|---------------|
|  pure white glossy | 5381 70 | 1/5 | | 4010337122395 |
|  pure white matt (lacquered) | 5381 72 | 1/5 | | 4010337122418 |
|  anthracite (lacquered) | 5381 73 | 1/5 | | 4010337122487 |
|  black matt (lacquered) | 5381 74 | 1/5 | | 4010337122500 |
|  grey matt (lacquered) | 5381 76 | 1/5 | | 4010337122517 |

Merkmale

- Manual and time-controlled operation of e.g. blinds, shutters, awnings, lighting or fans.
- Operation and programming with mobile end device (smartphone or tablet) via Bluetooth® using the Gira System 3000 App.
- Operation on System 3000 switching, dimming or blind insert and 3-wire auxiliary unit.

Functions on the top unit

- Operation of hangings and lighting.
- The blocking function blocks operation of the auxiliary unit and deactivates automatic mode.
- Activate/deactivate automatic mode.
- The runtime and an individual intermediate position can be saved using the System 3000 blind controller insert.
- Switch-on brightness of lighting can be saved using System 3000 dimming insert or DALI Power control unit.
- Adjustable night mode. Status LED and function LED are not lit up continuously.

Functions with the Gira System 3000 app

- Operation of hangings and lighting with status feedback.
 - Display the current hanging position or dimmer setting.
 - Programming of up to 40 individual switching times.
 - Blind or slat positions or switching and dimming values can be stored for each switching time.
 - Switching times can be copied to other devices.
 - Switching at sunrise or sunset (astro function).
 - Astro time can be optimised by determining the location.
 - Astro time shift adjustable.
 - Random function.
 - Automatic date and time refresh when connecting smartphones or tablets.
 - Password protection possible for time programs and configuration.
 - Save a curtain position, curtain runtime, slat reversal time.
 - Changeover to inverse operation possible for blind inserts.
 - Maximum brightness and minimum brightness adjustable for dimming insert.
 - Optional: Sun protection and twilight functions are possible with System 3000 brightness and temperature sensor Bluetooth®.
-

Technische Daten

| | |
|----------------------|----------------------|
| Accuracy | |
| - Per month: | ± 10 s |
| Power reserve: | approx. 4 h |
| Wireless frequency: | 2.402 to 2.480 GHz |
| Transmission power: | max. 2.5 mW, class 2 |
| Transmission range: | typically 10 m |
| Ambient temperature: | -5 °C to +45 °C |

Hinweise

- The time is updated upon connection to the Gira System 3000 app.
-