




## System 3000 blind timer and timer BT System 70



Spezifikation	Bestell-Nr.	VE	PS	EAN
 pure white glossy	5381 70	1/5		4010337122395
 pure white matt (lacquered)	5381 72	1/5		4010337122418
 anthracite (lacquered)	5381 73	1/5		4010337122487
 black matt (lacquered)	5381 74	1/5		4010337122500
 grey matt (lacquered)	5381 76	1/5		4010337122517

### Merkmale

- Manual and time-controlled operation of e.g. blinds, shutters, awnings, lighting or fans.
- Operation and programming with mobile end device (smartphone or tablet) via Bluetooth® using the Gira System 3000 App.
- Operation on System 3000 switching, dimming or blind insert and 3-wire auxiliary unit.

#### Functions on the top unit

- Operation of hangings and lighting.
- The blocking function blocks operation of the auxiliary unit and deactivates automatic mode.
- Activate/deactivate automatic mode.
- The runtime and an individual intermediate position can be saved using the System 3000 blind controller insert.
- Switch-on brightness of lighting can be saved using System 3000 dimming insert or DALI Power control unit.
- Adjustable night mode. Status LED and function LED are not lit up continuously.

#### Functions with the Gira System 3000 app

- Operation of hangings and lighting with status feedback.
  - Display the current hanging position or dimmer setting.
  - Programming of up to 40 individual switching times.
  - Blind or slat positions or switching and dimming values can be stored for each switching time.
  - Switching times can be copied to other devices.
  - Switching at sunrise or sunset (astro function).
  - Astro time can be optimised by determining the location.
  - Astro time shift adjustable.
  - Random function.
  - Automatic date and time refresh when connecting smartphones or tablets.
  - Password protection possible for time programs and configuration.
  - Save a curtain position, curtain runtime, slat reversal time.
  - Changeover to inverse operation possible for blind inserts.
  - Maximum brightness and minimum brightness adjustable for dimming insert.
  - Optional: Sun protection and twilight functions are possible with System 3000 brightness and temperature sensor Bluetooth®.
- 

## Technische Daten

Accuracy	
- Per month:	± 10 s
Power reserve:	approx. 4 h
Wireless frequency:	2.402 to 2.480 GHz
Transmission power:	max. 2.5 mW, class 2
Transmission range:	typically 10 m
Ambient temperature:	-5 °C to +45 °C

---

## Hinweise

- The time is updated upon connection to the Gira System 3000 app.
-