


Pushbutton sensor 3 Basis, 2-gang for KNX Gira F100



Spezifikation	Bestell-Nr.	VE	GBP/Stück o. MWSSt.	PS	EAN
 pure white glossy	2022 112	-	-	-	4010337081685

Merkmale

- Installation on bus coupler 3.
- Safeguarded from disassembly because it is screw-fastened.
- Rocker function: Switching, dimming, blind, value transmitter 1-byte, and scene auxiliary unit.
- Two blue status LEDs on each operating surface.
- White operating LED.
- Operating LED and status LED function can be parameterised.

Technische Daten

Ambient temperature:	-5 °C to +45 °C
Protection class:	III

Hinweise

- Professional inscription by the Gira inscription service www.beschriftung.gira.de.

Lieferumfang

- Plain inscription labels included.