

## System 3000 blind controller insert without auxiliary input



| Spezifikation   | Bestell-Nr. | VE  | GBP/Stück o. MWSt. | PS | EAN           |
|---|-------------|-----|--------------------|----|---------------|
|  | 5415 00     | 1/5 | 78.63              | 02 | 4010337027416 |

### Merkmale

- Control of electrically operated blinds, shutters and awnings.
- An individual intermediate position can be saved together with a top unit.
- Controlling a motor, e.g. to set the end positions, can be done without a top unit.
- Polarity reversal function for the outputs for simplified start-up.
- Operation with neutral conductor connection.

Combination with RF Multi operating top unit, 1-gang / 2-gang for KNX

- Blind actuator, 1-gang.
- Sensor channel, 1-gang or 2-gang.
- Local control of System 3000 insert possible.
- Wireless control of other devices for KNX possible as a sensor.
- Temperature detection.
- Insert function selection: Curtain type selectable, safety function (wind, rain, frost alarm), sun protection function, scene function, blocking function.

### Technische Daten

|                           |                                     |
|---------------------------|-------------------------------------|
| Rated voltage:            | AC 230 V, 50/60 Hz                  |
| Connected load of motors: | 700 W                               |
| Standby mode:             | 0.1 W to 0.5 W                      |
| Installation:             | in device box pursuant to DIN 49073 |
| Installation depth:       | 24 mm                               |
| Ambient temperature:      | -5 °C to +45 °C                     |