© Copyright by
Gira Giersiepen GmbH & Co. KG
All rights reserved



**Cut-off relay, 2-gang**



| Specification | Order No. | Packing unit | PS | EAN |
|---|---|---|---|---|
|  DRA | 0861 00 | 1 | | 4010337861003 |

**Features**

- Simultaneous control of more than one blind drive.
- In each case, two drives are electrically decoupled with one cut-off relay.
- With two auxiliary inputs for the individual operation of the blinds and a central input for a central function, e.g. of a timer or for implementation of central control systems in the event of distribution among several RCCBs.

**Technical data**

| | |
|---|---|
| Rated voltage: | AC 230 V, 50 Hz |
| Switching current: | 4 A, cos φ ≥ 0.8 ind., 100% switch-on duration |
| Connections | |
| - Power supply: | 2 x screw terminal |
| - Central: | 2 x screw terminal |
| - Drive 1, 2: | 2 screw terminals each |
| - Auxiliary unit 1, 2: | 1 screw terminal each |
| Ambient temperature: | -25 °C to +70 °C |

**Notes**

- The DRA cut-off relay is installed on a cap profile rail.

**Dimensions**

| | |
|---|---|
| Modular width (MW): | 2,5 |

Illustrations are similar and may deviate from originals.