

## Pushbutton sensor 3 Basis, 2-gang for KNX Gira F100



Spezifikation	Bestell-Nr.	VE	PS	EAN
 pure white glossy	2022 112	1/5		4010337081685

### Merkmale

- Installation on bus coupler 3.
- Safeguarded from disassembly because it is screw-fastened.
- Rocker function: Switching, dimming, blind, value transmitter 1-byte, and scene auxiliary unit.
- Two blue status LEDs on each operating surface.
- White operating LED.
- Operating LED and status LED function can be parameterised.

### Technische Daten

Ambient temperature:	-5 °C to +45 °C
Protection class:	III

### Hinweise

- Professional inscription by the Gira inscription service [www.beschriftung.gira.de](http://www.beschriftung.gira.de).

### Lieferumfang

- Plain inscription labels included.