© Copyright by
Gira Giersiepen GmbH & Co. KG
All rights reserved

www.gira.com

Motion detector 1.10 m for Gira One

Specification	Order No.	Packing unit	PS	EAN
pure white glossy	2038 03	1		4010337125525
pure white matt	2038 27	1		4010337125532
anthracite	2038 28	1		4010337125600
black matt (lacquered)	2038 005	1		4010337125624
grey matt (lacquered)	2038 015	1		4010337125631

Features

- Motion detector (with passive infrared sensor/PIR) for Gira One.
- For automatic switching of Gira One actuators depending on movement and brightness.
- The delay time of the Gira One consumer is configured via the relevant actuator channel in the Gira Project Assistant (GPA).
- Integrated temperature sensor for measuring the room temperature.
- Integrated local button to control the Gira One consumer: Switching, staircase and scene.
- Commissioning the motion detector with the Gira Project Assistant (GPA) version 5.2.
- Encrypted data transfer between the Gira One devices.

Features of the motion detector

- Large detection range (up to 238 m^2).
- Expansion of the detection range with additional motion detectors.
- It is possible to limit the detection range.
- It is possible to configure the sensitivity of the sensors.
- Walking test function to help in planning and adjusting the PIR detection range.
- Mixed light measurement suitable for fluorescent lamps (FL/PL/ESL), halogen/light bulbs and LEDs.

Illustrations are similar and may deviate from originals.

© Copyright by
Gira Giersiepen GmbH & Co. KG
All rights reserved

Room temperature

- Temperature adjustment for the integrated temperature sensor.

LED display

- Status LED function selection: always OFF, movement display.

Notes

- Can be updated via the Gira Project Assistant (GPA).
- The motion detector is not suitable for alarm messages in VdS-compliant alarm systems.
- KNX Data Secure compatible.