

RF/TP media coupler or RF repeater for KNX



| Spezifikation | Bestell-Nr. | VE | PS | EAN |
|---|-------------|----|----|---------------|
|  | 5110 00 | - | - | 4010337017264 |

With the KNX RF system devices, the RF pushbutton sensors for KNX and RF hand-held transmitters for KNX are incorporated and parameterised in the KNX structure via the ETS.

Merkmale

- Interface between wired KNX products (TP) and KNX RF wireless products.
- Can be configured using ETS as a media coupler, media coupler with repeater, segment coupler or repeater (depending on firmware version used and ETS version).
- Use as a segment coupler possible in the event of start-up with ETS from version 6.0.5 or higher (from index level I04 or higher or following a firmware update for index levels I00 to I03).
- Devices can be updated. Firmware updates (e.g. I00 to I04) can be performed using ETS.
- Supports KNX Data Secure communication (KNX Data Secure telegrams can be processed and filtered, forwarded or blocked according to the settings).
- Fast communication between KNX products in main line and line (long frame support with ETS5 and higher).

Technische Daten

| | |
|----------------------|------------------|
| KNX medium: | RF1.R, TP1-256 |
| Start-up mode: | S mode |
| Rated voltage: | |
| Ambient temperature: | -20 °C to +45 °C |
| Wireless frequency: | 868.3 MHz |
| Transmission power: | max. 20 mW |
| Range (free field): | approx. 100 m |

Hinweise

- KNX Data Secure compatible.

Lieferumfang

- Connection and junction terminal for KNX included with delivery.
