GIRA Parts list

catalogue.gira.com

© Copyright by
Gira Giersiepen GmbH & Co. KG
All rights reserved

www.gira.com

Pushbutton sensor 3 Basis, 1-gang for KNX with start-up rocker

Spezifikation	Bestell-Nr.	VE	PS	EAN
	5111 00	1/5	06	4010337086802

Merkmale

- Installation on bus coupler 3.
- Safeguarded from disassembly because it is screw-fastened.
- Rocker function: Switching, dimming, blind, value transmitter 1-byte, and scene auxiliary unit.
- White operating LED.
- Two red status LEDs per operating surface.
- Inscription space illumination for rocker sets with inscription space.
- Function of inscription space illumination and status LED can be configured.

Technische Daten

Ambient temperature:	-5 °C to +45 °C
Protection class:	III

Hinweise

- Professional inscription by the Gira inscription servicewww.beschriftung.gira.de.
- The pushbutton sensor is delivered with a program-neutral start-up rocker. The suitable rocker set for the switch range must be ordered separately.

Lieferumfang

- Plain inscription labels included.

Abbildungen sind ähnlich und können vom Original abweichen.